

Four-wave mixing of linear waves and solitons in fibres with higher order dispersion

A.V. Yulin, D.V. Skryabin, and P.St.J. Russell

Department of Physics, University of Bath, Bath BA2 7AY, UK

(February 2, 2008)

We derive phase-matching conditions for four-wave mixing between solitons and linear waves in optical fibres with arbitrary dispersion and demonstrate resonant excitation of new spectral components via this process.

The use of any optical system, including fibres, for frequency conversion relies on the ability to satisfy so-called phase matching conditions, which critically depend on the dispersive properties of the system, and on strong enough nonlinear properties, to allow reduction in the threshold pump power. The recent surge of interest in theoretical and experimental studies of optical parametric processes in photonic crystal fibres (PCFs) [1–7] is related to their high nonlinearities, achieved by reduction in the core size [8], and to the possibility of dispersion control by suitable design of the photonic crystal cladding [2].

Here we study parametric generation of new frequencies resulting from four-wave mixing (FWM) of solitons and continuous waves (cw's) in optical fibres under conditions where the effects of higher order dispersion are important, i.e., when pulses are short and/or the frequency dependence of the group velocity dispersion (GVD) is steep. Interest to this problem arises from the fact that the Fourier components of a soliton are dispersionless, while freely propagating cw's are strongly dispersive. Therefore the phase-matching conditions are expected to be satisfied at frequencies different from those generated by the mixing of cw's. Addressing this issue is timely because of the availability of strongly nonlinear small-core PCFs [7,8], which decrease the threshold for observing of parametric processes by one to two orders of magnitude compared to conventional fibres: $\gamma_{conven} \sim 10^{-3} \text{W}^{-1}\text{m}^{-1}$, $\gamma_{pcf} \sim 10^{-2}$ to $10^{-1} \text{W}^{-1}\text{m}^{-1}$, where γ is the nonlinear fibre parameter [9]. Strongly nonlinear PCFs have already been used to demonstrate the coupling of solitons and cw radiation in: supercontinuum generation [1,6], strong red and blue resonant, or Cherenkov, radiation from solitons [6,7] and cancellation of the soliton self-frequency shift by the spectral recoil [7]. Note, that it is natural to expect that FWM of solitons and cw radiation is one of the many nonlinear processes contributing to the shape of the supercontinuum spectra.

The problem of mixing of solitons and cw using the idealized nonlinear Schrödinger equation (NLS), i.e., with higher order dispersion disregarded, has been analyzed in a number of papers in the past [10–15]. In these cases several exact analytical solutions for a soliton sitting on the cw background were found [14,15] and different perturbation techniques suggested [10–13]. However, none of these studies have addressed the issue of generation of

new frequencies by FWM of solitons and cw light – the central focus of this paper.

We assume that the dynamics of the dimensionless amplitude $A(t, z)$ of the fundamental fiber mode is governed by the generalized NLS equation [2]

$$\partial_z A = iD(i\partial_t)A + iA \int_{-\infty}^{+\infty} R(t')|A(t-t', z)|^2 dt'. \quad (1)$$

The dispersion operator in Eq. (1) is given by

$$D(i\partial_t) \equiv \sum_{m=2}^M \frac{\tau^{2-m} \partial_\omega^{m-2} \beta_2(\omega_0)}{m! |\beta_2(\omega_0)|} [i\partial_t]^m, \quad (2)$$

where τ is the pulse duration and ω_0 is the reference frequency. To avoid any ambiguity in the analytical expressions we adopt the convention of using round brackets (..) to indicate the arguments of functions or operators and [...], {...} for all other purposes. $R(t)$ is the response function of the material, which includes instantaneous Kerr and delayed Raman nonlinearities:

$$R(t) = [1 - \theta]\Delta(t) + \theta\alpha\Theta(t)e^{-t/\tau_2} \sin(t/\tau_1) \quad (3)$$

Here $\Delta(t)$ and $\Theta(t)$ are, respectively, delta and Heaviside functions, $\alpha = [\tau_1/\tau_2 + \tau_2/\tau_1]/\tau_2$, $\theta = 0.18$, $\tau_1 = 12.2fs/\tau$, $\tau_2 = 32fs/\tau$ [9]. t is the time in the reference frame moving with the group velocity $v_0 = v(\omega_0)$ and measured in the units of τ : $t = [T - z/v_0]/\tau$, where T is the physical time. $z = Z/L_{gvd}$, where Z is the distance along the fiber and $L_{gvd} = \tau^2/|\beta_2(\omega_0)|$ is the GVD length. The field amplitude A is measured in units of $N/\sqrt{\gamma L_{gvd}}$, where N^2 is the ratio of the peak power of the pump pulse to the peak power of a fundamental soliton with duration τ .

The dispersive properties of the soliton and linear cw are crucial for the following, so we now discuss them in some detail. Looking for a linear wave solution of (1) in the form $A \sim e^{iD_x z - i\delta_x t}$ we find $D_x = D(\delta_x)$. In what follows the subscript x can take any convenient notation. E.g., δ_s and δ_{cw} correspond below to the frequency shifts of the soliton and cw-pump, respectively. Thus the physical wave number of a linear wave with frequency $\omega_0 + \delta_x/\tau$ is given by $k_x = k(\omega_0) + D_x/L_{gvd}$. Plotting $k_x - k(\omega_0)$ vs δ_x one simply recovers the dispersion profile of the fibre. The single soliton solution

$$A = F(\xi)e^{-i\delta_s t + i[D_s + q]z}, \quad F(\xi) = \sqrt{2q} \text{sech}(\xi/r) \quad (4)$$

satisfies Eq. (1) if all derivatives of the function $F(\xi)$ higher than second are disregarded, $\theta = 0$, and $D_s'' < 0$, i.e., the GVD at the soliton frequency is anomalous. Here $\xi = t - D_s'z$, $r = \sqrt{-D_s''/(2q)}$, $'$ denotes the derivative with respect to δ and $q > 0$ is the additional shift of the soliton wave number. Representing $F(\xi)$ through the inverse transform of its Fourier image $\tilde{F}(\delta)$, i.e. $F = \int d\delta \tilde{F} e^{i\xi[\delta_s - \delta]}$, one finds that the wave number of a Fourier component of the soliton with frequency $\omega_0 + \delta_x/\tau$ is given by $k_{s/x} = k(\omega_0) + \{D_s + q - [\delta_s - \delta_x]D_s'\}/L_{gvd}$. Thus plotting $k_{s/x} - k(\omega_0)$ vs δ_x will give the tangent line to the curve $k_x - k(\omega_0)$ taken at the point $\delta_x = \delta_s$ and shifted up by q . The linear dependence of $k_{s/x}$ on δ_x is a reflection of the dispersion-free nature of solitons.

We seek solutions of Eq. (1) in the form

$$A = \{F(\xi) + g(z, \xi)\} e^{iz[D_s + q] - i\delta_s t}, \xi \equiv t - zD_s'. \quad (5)$$

Assuming that g is a quasi-linear wave we derive

$$ip = \partial_z g - i\tilde{D}(i\partial_\xi)g - i2F^2g - iF^2g^*, \quad (6)$$

where $\tilde{D}(i\partial_\xi) = -q - D_s - iD_s'\partial_\xi - D(i\partial_\xi + \delta_s)$ and $p = [D(i\partial_\xi + \delta_s) - D_s - iD_s'\partial_\xi + 1/2D_s''\partial_\xi^2]F$. Now we split g into two parts

$$g = we^{i\phi} + \psi, \quad \phi = z\tilde{D}(\delta_{cw} - \delta_s) + \xi[\delta_s - \delta_{cw}] \quad (7)$$

The w -term in Eq. (7) is the weak cw pump, which obeys Eq. (6) with $p = F = 0$. The ψ -term is the field generated through the mixing of the soliton and cw pump and by the soliton itself. Seeking ψ in the form $\psi = \psi_p + \psi_+ e^{iz\tilde{D}(\delta_{cw} - \delta_s)} + \psi_-^* e^{-iz\tilde{D}(\delta_{cw} - \delta_s)}$ we find that ψ_p obeys

$$i \begin{bmatrix} p \\ -p^* \end{bmatrix} = \left\{ \partial_z + i\hat{\mathcal{L}} \right\} \begin{bmatrix} \psi_p \\ \psi_p^* \end{bmatrix}, \quad (8)$$

and $\psi_\pm$ are governed by the system of coupled equations

$$iF^2 w e^{i\xi[\delta_s - \delta_{cw}]} \begin{bmatrix} 2 \\ -1 \end{bmatrix} = \left\{ \partial_z + i\hat{\mathcal{L}} + i\hat{\mathcal{W}} \right\} \begin{bmatrix} \psi_+ \\ \psi_- \end{bmatrix}, \quad (9)$$

where

$$\hat{\mathcal{L}} = \begin{bmatrix} -\tilde{D}(i\partial_\xi) - 2F^2 & -F^2 \\ F^2 & \tilde{D}(-i\partial_\xi) + 2F^2 \end{bmatrix},$$

$$\hat{\mathcal{W}} = \tilde{D}(\delta_{cw} - \delta_s) \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix}.$$

Eq. (8) does not depend on the cw-pump and it is known to describe the emission of non-localized dispersive waves from solitons – so-called resonant or Cherenkov radiation – in fibres with zero GVD points [6,7,16–18]. This radiation exists because the continuous part of the spectrum of the operator $\hat{\mathcal{L}}$ has a zero eigenvalue, which ensures resonance with the forcing term p . The operator $\hat{\mathcal{L}} + \hat{\mathcal{W}}$

is expected to have several different resonances, a situation which to our knowledge has not previously been considered. These resonances are driven by FWM between the soliton and the cw, see the left-hand side in Eq. (9). To find continuous spectra of $\hat{\mathcal{L}}$ and $\hat{\mathcal{L}} + \hat{\mathcal{W}}$ we neglect the F^2 -terms and look for eigenfunctions in the form $\psi_p \sim e^{i\kappa z + i[\delta_s - \delta]\xi}$ and $\psi_\pm \sim e^{\pm i\kappa z \pm i[\delta_s - \delta]\xi}$. Assuming that the wave numbers of the continuum modes are matched with the wave numbers of the driving terms in Eqs. (8,9), i.e. $\kappa = 0$, we find:

$$q + D_s - [\delta_s - \delta]D_s' = D(\delta), \quad (10)$$

$$\pm D_{cw} \mp \{q + D_s - [\delta_s - \delta_{cw}]D_s'\} + \{q + D_s - [\delta_s - \delta]D_s'\} = D(\delta). \quad (11)$$

Eqs. (10,11) are the equations for δ . The roots of these equations, which can be easily found graphically, yield the frequencies of the emitted radiation. The right-hand side $D(\delta)$ is simply the dispersion of linear waves, which is a nonlinear function of δ . The left-hand sides are straight lines. Fitting the experimentally measured dispersion characteristics of the fibres usually results in a very high order polynomial for $D(\delta)$ [2,7]. Here, however we use the simplest illustrative example, when only the third order dispersion is included, i.e. $D(\delta) = -\delta^2/2 + \epsilon\delta^3$, $\epsilon = \partial_\omega \beta_2(\omega_0)/(6\tau|\beta_2(\omega_0)|)$. This model accurately describes regions where the frequency dependence of $\beta_2(\omega)$ is quasi-linear – typical for telecom and PCF fibres, see, e.g., [7]. Figs. 1(a) and (b) show plots of the right- and left-hand sides of Eqs. (10,11). Eq. (10) gives the Cherenkov resonance [6,7,16–18], which does not depend on the cw-pump. The roots resulting from Eqs. (11), however, are determined by the cw-pump. Depending on the value of δ_{cw} Eqs. (11) produce either two or four new roots, see Figs. 1(a),(b). Assuming that $\delta = \delta_{cw}$, we find that Eq. (11) with $+$ is satisfied, which means that one of the new roots always coincides with δ_{cw} . Clearly the position of these new resonances strongly depends on, and can be controlled by, the frequency of the cw-pump and by engineering the linear dispersion profile of the fibres.

The four-wave mixing nature of the new resonances becomes clear if we make use of the expressions for the wave numbers of the dispersive waves and the Fourier components of the soliton (see the discussion around Eq. (4)). Indeed, Eqs. (11) can be rewritten in the form

$$\pm[k_{cw} - k_{s/cw}] + k_{s/rad} = k_{rad}. \quad (12)$$

Here k_{rad} , k_{cw} are wavenumbers of the resonant radiation and the cw-pump, and $k_{s/rad}$, $k_{s/cw}$ are the wavenumbers of the Fourier components of the soliton at the frequencies of the resonant radiation and the cw-pump.

To confirm our analytical findings we have carried out a series of numerical experiments with parameters close to the ones in [7]. Comparing Figs. 1 (a),(b) with 1 (c),(d) one sees excellent agreement between the analytical predictions and the frequencies emerging from the

modelling of (1). The efficiency of excitation of the new frequencies strongly depends on the choice of δ_s and δ_{cw} relative to each other and to the zero GVD point. This explains why not all the resonances are observed simultaneously. Changing $\delta_{cw,s}$ we have been able to observe all of the newly predicted resonances. Theoretical analysis of this problem is possible within the framework of Eq. (7) and we leave it for a future study. The cw powers required to observe the new FWM resonances are of the order or less than 1W, see the Fig. 1 caption.




FIG. 1. Resonance frequencies (a,b) calculated from Eqs. (10,11) and supporting numerical modelling (c,d). Straight/curved lines in (a,b) are the left/right-hand sides of Eqs. (10,11). Choosing $\omega_0 = 2\pi \times 240\text{THz}$ and the fibre parameters from [7] we find $\beta_2 = -47\text{ps}^2/\text{km}$ and $\partial_\omega\beta_2 = -0.7\text{ps}^3/\text{km}$. $\delta_s = 0$, $w = 0.1$, $\delta_{cw} = -15$ for (a,c) and $\delta_s = -4$, $w = 0.3$, $\delta_{cw} = -40$ for (b,d). Other parameters are $\tau = 170\text{fs}$, $q = 4$, $N = 1.5$. For $\gamma = 0.05(\text{Wm})^{-1}$ this corresponds to the pulse peak power 225W, the cw-power 0.12W for (c) and 1.2W for (d). The full lines in (c,d) corresponds to $\theta = 0$, i.e. Raman is off, and the dashed lines to $\theta = 0.18$, i.e. Raman is on. The propagation distance is 2.8m (c) and 16m (d). The top axes are marked in wavelength units.

We have analyzed FWM between solitons and cw-pump in fibres with higher order dispersion and predicted the generation of new frequencies, which can be controlled by tuning the cw-pump. In addition to their fundamental significance, our results have important im-

plications for the generation of laser light and broad-band supercontinua in new frequency ranges.

This work is partially supported by the EPSRC grant GR/S20178/01.

-
- [1] J.K. Ranka, R.S. Windeler, and A.J. Stentz, *Opt.Lett.* **25**, 25 (2000).
 - [2] W.H. Reeves, D.V. Skryabin, F. Biancalana, J.C. Knight, P.St.J. Russell, F.G. Omenetto, A. Efimov, and A.J. Taylor, *Nature* **424**, 511 (2003).
 - [3] F. Biancalana, D.V. Skryabin and P.St.J. Russell, *Phys. Rev. E* **68**, 046603 (2003).
 - [4] J.D. Harvey, R. Leonhardt, S. Coen, G.K.L. Wong, J.C. Knight, W.J. Wadsworth and P.St.J. Russell, *Opt. Lett.* **28**, 2225 (2003).
 - [5] J.M. Dudley, L. Provino, N. Grossard, H. Maillotte, R.S. Windeler, B.J. Eggleton, and S. Coen, *J. Opt. Soc. Am. B* **19**, 765 (2002).
 - [6] J. Herrmann, U. Griebner, N. Zhavoronkov, A. Husakou, D. Nickel, J.C. Knight, W.J. Wadsworth, P.St.J. Russell, and G. Korn, *Phys. Rev. Lett.* **88**, 173901 (2002).
 - [7] D.V. Skryabin, F. Luan, J.C. Knight, and P.St.J. Russell, *Science* **301**, 1705 (2003).
 - [8] V. Finazzi, T.M. Monro, and D.J. Richardson, *J. Opt. Soc. Am. B* **20**, 1427 (2003).
 - [9] G.P. Agrawal, *Nonlinear Fiber Optics* (Academic Press, San Diego, 2001).
 - [10] A.Hasegawa and Y. Kodama, *Opt. Lett.* **7**, 285 (1982).
 - [11] H.A. Hauss, F.I. Khatri, W.S. Wong, E.P. Ippen, K.R. Tamura, *IEEE J. QE* **32**, 917 (1996).
 - [12] J.P. Gordon, *J. Opt. Soc. Am. B* **9**, 236 (1992).
 - [13] Y. Kominis and K. Hizanidis, *J. Opt. Soc. Am. B* **21**, 562 (2004).
 - [14] N. Akhmediev and S. Wabnitz, *J. Opt. Soc. Am. B* **9**, 236 (1992).
 - [15] Q.H. Park and H.J. Shin, *Phys. Rev. Lett.* **82**, 4432 (1999).
 - [16] P.K.A. Wai, H. H. Chen, and Y. C. Lee, *Phys. Rev. A* **41**, 426 (1990).
 - [17] V.I. Karpman, *Phys. Rev. E* **47**, 2073 (1993).
 - [18] N. Akhmediev and M. Karlsson, *Phys. Rev. A* **51**, 2602 (1995).